

# SS651-023



## FEATURES & BENEFITS

- Combine small size with big power
- Ideal for volunteers and vehicles with limited mounting space
- Wail, Yelp, Air Horn, Phaser, and Manual
- Positive and negative switching for Auxiliary inputs
- 20 programmable siren tones (Simulated mechanical wail and manual, eight air horn tones)
- Drives one 100 watt speaker
- New connector requires no special terminals allowing you to retrofit any old siren harness install with a wire stripper and screw driver
- Auxiliary enable can be used to enable a siren/air horn tone; or for duplexed hands free tone cycling
- Dip switches and push button for option selection
- High and low voltage shutdown protection
- Diagnostic LED
- Self-resetting circuit protection against speaker shorts
- Replaceable fuse
- Ships complete with positive locking connector, hardware, and instructions
- Dimensions: SS651 - 2"H x 5 <sup>7</sup>/<sub>16</sub>"W x 5 <sup>13</sup>/<sub>64</sub>"D, SS651-CH - 2 <sup>1</sup>/<sub>4</sub>"H x 3"W x 1 <sup>9</sup>/<sub>16</sub>"D
- Output: 100 watts (1 speaker)
- Voltage: 10 - 16V DC
- Frequency: 675-3000Hz
- Amp draw: 8 amps
- Lighting outputs: 2
- Approvals: Exceeds acoustical and environmental requirements, SAE J1849, California Title 13

PART	DESCRIPTION
SS651-023	Four mode economy siren separate switch panel

